

PP10 1RU SURGE FILTER



Novaris Plug-in Surge Filters plug into a standard mains outlet socket to provide premium protection for sensitive or critical electronic equipment. The PP10 1RU series is designed for rack mount installation to protect computer and communications equipment.



- ✓ LED status
- ✓ All mode protection
- ✓ Three stage filter
- ✓ Safe metal enclosure

PP10A8-50 1RU

Specifications

Nominal voltage	U_0	230 V / 50 Hz - 60 Hz
Maximum continuous voltage AC	U_c	275 V / 50 Hz - 60 Hz
Maximum load current	I_L	10 A
L-N Maximum discharge current (8/20 μ s)	I_{max}	50 kA
L-N Nominal discharge current (15 x 8/20 μ s)	I_n	20 kA
L-N Voltage protection level @ 3kA (8/20 μ s)	U_p	< 600 V
N-PE Nominal discharge current (15 x 8/20 μ s)	I_n	20 kA
N-PE Voltage protection level @ 1kV / μ s	U_p	< 800 V
Number of outlets		8
Dimensions		W 484 mm x D 220 mm x H 44mm